



TA-25

18-25 dB UHF/VHF/FM Distribution Amplifier



Features

- Cost-effective wide-frequency bandwidth amplifier
- 68 off-air channel range (54 to 108 MHz) suitable for small to large MATV-SMATV systems
- 7 dB sloped output across band provides low harmonic distortion
- -20 dB FM trap switch (88 to 108 MHz) filters high level local FM radio stations reducing harmonic distortion
- Heave gauge rugged shielded wall-mount case
- Convenient and compact design allows quick and easy installation
- Front Panel LED Power Indicator

Specifications

TA-25

BANDWIDTH		54-108 MHz	
		174-216 MHz	
		470-806 MHz	
GAIN		18-25 dB	
MAXIMUM OUTPUT (15 Channels)	VHF	25 dBmV	
	UHF	18 dBmV	
FLATNESS		7 dB	
NOISE FIGURE	VHF	5 dB	
	UHF	7 dB	
POWER INPUT		117 VAC	
POWER FREQUENCY		60 Hz	
POWER REQUIRED		4.5W	
WEIGHT		1.2 lbs (0.54 kg)	
TOTAL # OF CHANNELS	INPUT LEVEL	VHF OUTPUT LEVEL	UHF OUTPUT LEVEL
7	22 dBmV	47 dBmV	40 dBmV
15	19 dBmV	32 dBmV	25 dBmV

Ordering Information

Part Number	Description
TA-25	18-25 dB UHF/VHF/FM Distribution Amplifier

Products or features contained herein may be covered by one or more U.S. or foreign patents. Other non-ATX product and company names mentioned in this data sheet are the property of their respective companies.

© 2018 ATX Networks
Information in this document is subject to change without notice.
Rev. 09/18 (ANW1318)



ATX Networks

1-501 Clements Road West, Ajax, ON L1S 7H4 Canada
Tel: 905.428.6068 | Toll Free: 800.565.7488 | support@atxnetworks.com